

# LMD-120A

**DYNALCO**  
CONTROLS

## Current Loop-Powered Digital Indicator

*Easy to use. Powered by the 4–20 mA signal loop input; requires no external ac or dc.*

**2-Year  
Warranty**



LR45322  
Class I, Division 1,  
Groups A, B, C, & D

*\*See Third-Party Approvals*



### FEATURES

- Standard SAE gasketed and spray-proof case; fits panels with 3<sup>3</sup>/<sub>8</sub> in. openings.
- High noise immunity; no power line or supply connections.
- Liquid crystal display (LCD); no outdoor fade-out; 0.4 in. high digits.
- Ease of calibration; field-adjustable to any readout range by integral multiturn zero and span potentiometers, decimal point switches, and fifth-digit fixed zero switch.
- Bipolar display; positive and negative readouts.
- Rugged and reliable.

### SPECIFICATIONS

**Input Signal:** 4 to 20 mA.

**Display:** 3½ digits (1 digit resolution) or 4½ digits (10-digit resolution), bipolar. The display can be extended to 4½ digits by entering a fixed zero in the least significant digit position via a user-selectable switch.

**Span and Zero Adjust:** 25-turn potentiometers permit adjustment of the display to any desired span from 100 up to 2000 units and for any required initial reading from –1000 to +1000. (4 mA input for initial reading; 20 mA input for maximum indication.)

**Typical calibrations:** 0 to +1999, –500 to +500, +800 to +1000, etc. The fifth digit (dummy zero) can be turned on for readouts up to +19990.



**Loop Burden:** Less than 2 volts, i.e. 100 Ω at 20 mA.

**Environment Temperature:** 0°F to +165°F (–18°C to +74°C).

**Weight:** 1 lb, maximum (0.454 kg).

**\*Third Party Approvals:** CSA: (LR45322) Class I, Division 1, Groups A, B, C, & D. *Intrinsically safe:* when connected through a CSA-certified single channel Zener barrier rated 28.5 volts maximum, 300 Ω minimum.

# OUTLINE DRAWING



## VIEW WITH PLUG REMOVED

Calibration Controls under plug (rear).  
 Switches 1, 2, & 3 control decimal points  
 as shown.

Switch 4 adds a dummy zero (fifth digit,  
 fixed zero) to extend range beyond  
 +1999, (to +19990).

## HOW TO ORDER

1. If factory calibration is desired, specify the *precise display range* that corresponds to the 4–20 mA input such as 0 to +500, –300 to +300, –800 to +1000, 0 to +8.00, etc.
2. Specify the required nameplate legend such as RPM, LBS, °F, %, PSI, or a blank legend strip to be marked or screened by the user.

**CRANE** **DYNALCO**  
**CONTROLS**

LMD-120A is a trademark of Dynalco Controls.  
 DYNALCO CONTROLS RESERVES THE RIGHT TO CHANGE THESE SPECIFICATIONS WITHOUT NOTICE.  
 FOR COMPLETE SPECIFICATION INFORMATION, CONTACT A DYNALCO REPRESENTATIVE.